

## IP67 Waterproof Exit Button With 6wires



S85022L

### What is a request to exit switch?

Request-to-exit (REX) devices are used in conjunction with access control systems to ensure that tenants are able to freely and safely exit an area. Many options such as exit buttons, hands-free infrared, or touchsensitive devices make it an ideal choice for releasing maglocks or door strikes.

### Specifications

<b>Dimensions:</b>	86x50mm
<b>Panel material:</b>	1.7mm thick, 304 stainless steel brushed panel
<b>Button material:</b>	304 stainless steel, silver cobalt
<b>Waterproof:</b>	IP67
<b>Current Rating:</b>	3A, 36VDC
<b>Voltage:</b>	DC12
<b>Output:</b>	6wires (NO/COM/NC/COM/+12V/GND)
<b>Mechanical Life:</b>	1000000 tested
<b>Weight:</b>	0.14KG

### Dimensions



### Access control switch knowledge small science

Normally open contact: It is usually in the off state, and it is connected after being pressed.

Normally closed contact: It is usually in the on state, and then it is disconnected after being pressed.

Self-reset: After pressing, the button will reset and bounce back as soon as the hand is released.

Self-locking type: The button is locked after being pressed, and the button can only bounce back after pressing it once.